

EU7000iS

(EU7000iSAT1)

FEATURES

- 7000 watts, 120/240V
- Perfect for home back up power, RVs, outdoor events, and more
- Super quiet
- Fuel efficient - runs up to 18 hours on 5.1 gal of fuel
- Convenient electric start
- Inverter - stable power for computers and more
- Fuel injected - better fuel efficiency and lower maintenance

MSRP
\$4889*

★★★★★ (156 reviews)

[Write a Review](#)

[Find a Dealer](#) ▶

 512

[Compare Models](#)

*Manufacturer's suggested retail price. Price excludes applicable taxes.
Dealer sets actual selling price.

[For full warranty details click here.](#)



Hover over image to zoom in



zoom



Features

Specs

Accessories

Applications

Manuals

Reviews

Engine	Honda GX390 EFI
Displacement	389cc
AC Output	120/240V 7000W max. (58.3/29.1A) 5500W rated (45.8/22.9A)
Receptacles	20A 125V GFCI Duplex (2), 30A 125V Locking Plug, 30A 125/250V Locking Plug
DC Output	N/A
Starting System	Recoil, electric
Fuel Tank Capacity	5.1 gal.
Run Time per Tankful	6.5 hrs.@ rated load, 18.0 hrs. @ 1/4 load
Dimensions (L x W x H)	33.4" x 27.6" x 28.4"
Noise Level	58 dB(A) @ rated load, 52 dB(A) @ 1/4 load
Dry Weight	261 lbs.
Residential Warranty	3 Years
Commercial Warranty	3 Years